Saga Logger handling at Receiving Site

Press and hold the **stop button** (1) for **5 seconds**, the shipment LED (2) lights up for 3 seconds.

Shipping mode (3) should change to **Stopping** or **Stopped**.

What is the battery status? (4)

Low power mode
Logger is now in low power mode.
Please charge device.

Charge the device by plugging it into a Controlant charging station/USB charging adapter/computer USB port until it reaches **minimum 15%** battery level.

Note that a charging period of 6 hours is required to fully charge the device from 0-100%.

>10%

What is the connection status? (5)

Press the stop button again in an area with stronger cellular reception.
If unsuccessful, wake up the device by plugging it into a Controlant charging station/USB charging adapter/ computer USB port, then unplug and wait for 10 minutes to see if the device connects to the Cloud.
If unsuccessful, proceed to a manual data upload at https://upload.controlant.com/ or contact support@controlant.com for assistance, stating your location and device ID number.

What is the alarm status? (6)

NO alarm icon

Alarm icon + Alarm LED blinking every 5s

Place the device in the assigned area for Controlant loggers, as they are reusable. Follow the agreed process to return the devices.

A temperature excursion has occurred, check your SOP and act accordingly.

Controlant Support
support@controlant.com
+354 517 0630